

FAA-420-RI-DIN Remote indicator for DIN application

www.boschsecurity.com



BOSCH
Invented for life



- ▶ 360° view, for both wall mount and ceiling mount
- ▶ Easy plug in installation
- ▶ Easy cabling thanks to cable ties bracket and all direction knock-out holes
- ▶ Long life and robust construction housing
- ▶ Efficient LED

The remote indicator is used when the automatic detector is installed in a place hidden or not visible, like in closed rooms, false ceilings or walls. It is recommended to mount the remote indicator in corridors or access pathways of the corresponding building sections or rooms.

The DIN version has a transparently red alarm display. The design of the remote indicator complies with the requirements of DIN 14623. Additionally, it features three operating modes:

- Operating Mode 1 with the indicator showing steady red light (please see note on current limitation).
- Operating Mode 2 with the indicator showing steady red light with internal current limitation.
- Operating Mode 3 with the indicator showing flashing red light.

Certifications and approvals

Region	Regulatory compliance/quality marks	
Europe	CPR	0786-CPR-21481 FAA-420-RI-DIN/ FAA-420-RI-ROW
Poland	ITB	020-UWB-2643/W FAA-420-RI-DIN / FAA-420-RI-ROW

Region	Regulatory compliance/quality marks	
Germany	VdS	G 215079 FAA-420-RI-DIN
Europe	CE	FAA-420-RI-DIN/-ROW

Installation/configuration notes

- You can connect only one detector per remote indicator. However, it is possible to indicate an alarm from more than one detector on an LSN bus via configuring the panel with the Remote Programming Software FSP-5000-RPS respectively.
- In LSN periphery the sum of all cable lengths between LSN devices and remote indicators as well as between LSN interface modules and conventional devices must not exceed 500 m.
- If you use unshielded cables, the cable length between LSN device (e.g. detector) and remote indicator is restricted to a maximum of 3 m.
- When connected to LSN detectors operate either in mode 1 or 3.
- If connected to a non-LSN detector, in operating mode 1 current has to be externally limited to max. 30 mA.

Parts included

Quantity	Component
1	Remote indicator

Technical specifications

Operating voltage	
• Operating mode 1	depends on current feed
• Operating mode 2	8.5 to 33 VDC
• Operating mode 3	11 to 33 VDC
Current feed for display	
• Operating mode 1	3 to 30 mA
• Operating mode 2	11 to 14 mA
• Operating mode 3	3 mA

Permissible wire gauge	0.6 to 1.0 mm
Dimensions	85 x 85 x 35 mm
Weight	65 g
Operating temperature	0 to +65°C
Permissible relative humidity	< 95% (non-condensing)
Degree of protection (IEC 60529)	IP40

Ordering information

FAA-420-RI-DIN Remote indicator for DIN application
 For applications where the automatic detector is not visible, or mounted in false ceilings/floors. This version complies with DIN 14623.
 Order number **FAA-420-RI-DIN**

Represented by:

Europe, Middle East, Africa:
 Bosch Security Systems B.V.
 P.O. Box 80002
 5600 JB Eindhoven, The Netherlands
 Phone: + 31 40 2577 284
 emea.securitysystems@bosch.com
 emea.boschsecurity.com

Germany:
 Bosch Sicherheitssysteme GmbH
 Robert-Bosch-Ring 5
 85630 Grasbrunn
 Germany
 www.boschsecurity.com

North America:
 Bosch Security Systems, Inc.
 130 Perinton Parkway
 Fairport, New York, 14450, USA
 Phone: +1 800 289 0096
 Fax: +1 585 223 9180
 onlinehelp@us.bosch.com
 www.boschsecurity.us

Asia-Pacific:
 Robert Bosch (SEA) Pte Ltd, Security Systems
 11 Bishan Street 21
 Singapore 573943
 Phone: +65 6571 2808
 Fax: +65 6571 2699
 apr.securitysystems@bosch.com
 www.boschsecurity.asia